

ON AN INVERSE BOUNDARY PROBLEM ARISING IN BRAIN IMAGING

YOUJUN DENG, HONGYU LIU, AND GUNTHER UHLMANN

ABSTRACT. We consider the inverse problem of recovering both an unknown electric current and the surrounding electromagnetic parameters of a medium from boundary measurements. This inverse problem arises in brain imaging. We show that we can recover both the source and the electromagnetic parameters if these are piecewise constant and the current source is invariant in a fixed direction or a harmonic function.

Keywords: Maxwell system, inverse source problem, inverse medium problem, identifiability and uniqueness, electroencephalography and magnetoencephalography

2010 Mathematics Subject Classification: 35Q60, 31B10, 35R30, 78A40

1. INTRODUCTION

1.1. Mathematical setup. We formulate precisely the problem that we are considering. We consider an inverse boundary value problem associated to the time depending Maxwell system.

Let B be a bounded domain in $\mathbb{R}^3$ with a $C^{1,1}$ -smooth boundary ∂B . Throughout, we let $\mathbf{x} = (\mathbf{x}_j)_{j=1}^3 \in \mathbb{R}^3$ denotes the space variable and t denotes the time variable. Let $\mathcal{J}(\mathbf{x}, t)$, $(\mathbf{x}, t) \in \mathbb{R}^3 \times \mathbb{R}_+ \rightarrow \mathbb{R}^3$ denotes a causal function such that $\mathcal{J}(\mathbf{x}, t) = 0$ for $(\mathbf{x}, t) \in \mathbb{R}^3 \setminus \overline{B} \times \mathbb{R}_+$. It models the current source. We characterize the electromagnetic (EM) medium by the electric permittivity $\epsilon(\mathbf{x})$, magnetic permeability $\mu(\mathbf{x})$ and electric conductivity $\sigma(\mathbf{x})$. $\epsilon(\mathbf{x})$ and $\mu(\mathbf{x})$ are positive scalar functions that are bounded below and above, and $\sigma(\mathbf{x})$ is a nonnegative scalar function that is bounded above, such that $\epsilon(\mathbf{x}) = \epsilon_0$, $\mu(\mathbf{x}) = \mu_0$ and $\sigma(\mathbf{x}) = 0$ for $\mathbf{x} \in \mathbb{R}^3 \setminus \overline{B}$, where ϵ_0 and μ_0 are positive constants. ϵ_0 and μ_0 are the EM parameters of the homogeneous background space $\mathbb{R}^3 \setminus \overline{B}$. Let $\mathcal{E}$ and $\mathcal{H}$ be both $\mathbb{R}^3$ -valued functions, which respectively model the electric and magnetic fields generated by the source current $\mathcal{J}$. We have the following Maxwell system,

$$\left\{ \begin{array}{l} -\epsilon(\mathbf{x})\partial_t \mathcal{E}(\mathbf{x}, t) + \nabla \times \mathcal{H}(\mathbf{x}, t) = \mathcal{J}(\mathbf{x}, t) + \sigma(\mathbf{x})\mathcal{E}(\mathbf{x}, t), \\ \mu(\mathbf{x})\partial_t \mathcal{H}(\mathbf{x}, t) + \nabla \times \mathcal{E}(\mathbf{x}, t) = 0 \quad (\mathbf{x}, t) \in \mathbb{R}^3 \times \mathbb{R}_+, \\ \mathcal{E}(\mathbf{x}, 0) = \mathcal{H}(\mathbf{x}, 0) = 0, \quad \mathbf{x} \in \mathbb{R}^3, \end{array} \right. \quad (1.1)$$

Associated with (1.1), we define a boundary measurement operator

$$\Pi_{\mathcal{J},\epsilon,\mu,\sigma}(\mathbf{x}, t) = (\mathcal{E}, \mathcal{H})(\mathbf{x}, t)|_{(\mathbf{x}, t) \in \partial B \times \mathbb{R}_+}, \quad (1.2)$$

where $(\mathcal{E}, \mathcal{H})$ is the pair of solutions to (1.1). The inverse problem that we are concerned with is to simultaneously recover $\mathcal{J}, \epsilon, \mu$ and σ by knowledge of $\Pi_{\mathcal{J},\epsilon,\mu,\sigma}$, namely

$$\Pi_{\mathcal{J},\epsilon,\mu,\sigma}(\mathbf{x}, t) \rightarrow (B; \mathcal{J}, \epsilon, \mu, \sigma). \quad (1.3)$$

In this paper, we aim to establish sufficient conditions for the following unique recovery result holding true

$$\Pi_{\mathcal{J}_1, \epsilon_1, \mu_1, \sigma_1} = \Pi_{\mathcal{J}_2, \epsilon_2, \mu_2, \sigma_2} \implies (\mathcal{J}_1, \epsilon_1, \mu_1, \sigma_1) = (\mathcal{J}_2, \epsilon_2, \mu_2, \sigma_2), \quad (1.4)$$

where $(\mathcal{J}_1, \epsilon_1, \mu_1, \sigma_1)$ and $(\mathcal{J}_2, \epsilon_2, \mu_2, \sigma_2)$ are two sets of admissible electric sources and EM medium parameters.

1.2. Background and motivation. In the physical setting, $(B; \epsilon, \mu, \sigma)$ denotes an inhomogeneous EM medium that is embedded in a homogeneous background space $(\mathbb{R}^3 \setminus \overline{B}; \epsilon_0, \mu_0)$. $\mathcal{J}$ denotes an electric current density that is located inside the body $(B; \epsilon, \mu, \sigma)$. The presence of the source $\mathcal{J}$ generates the EM fields $\mathcal{E}$ and $\mathcal{H}$ that propagate (nondestructively) outside the body B . The inverse problem (1.3) is concerned with the inference of the knowledge of the interior of the body B , which is a natural wave probing approach that has been widely adopted in many applications.

For the inverse problem (1.3) described above, if one assumes that the medium $(B; \epsilon, \mu, \sigma)$ is known, but $\mathcal{J}$ is unknown, then the problem is usually referred to as an inverse source problem; see [4, 11] and the references therein for relevant discussions. This inverse source problem is of particular significance to electroencephalography (EEG) and magnetoencephalography (MEG) (cf. [6, 7]), which are two important brain imaging methods. It is known that brain activity induce EM fields and the measurement of the induced EM fields can be used to understand the brain processes, which is actually modelled as the inverse source problem associated with (1.3). We are aware of some recovery results in the literature associated with EEG and MEG [1, 9, 10]. However, these articles deal with the recovery of the source term, corresponding to the neuronal current inside the brain, without considering the simultaneous recovery of the source and the surrounding medium. The inverse source problem is linear. If one assumes that $\mathcal{J}$ is known, but the medium $(B; \epsilon, \mu, \sigma)$ is unknown, then the corresponding inverse problem (1.3) is usually referred to as an inverse medium problem (cf. [8, 11, 15, 16, 20–22]). However, we would like to remark that the inverse medium problems considered in the literature are usually active in the sense that the measurement data are generated by sending EM fields from outside of the body and then by measuring the EM responses at the outside of the body as well. In this paper, we consider

the inverse problem (1.3) by assuming that both the source $\mathcal{J}$ and the surrounding medium $(B; \epsilon, \mu, \sigma)$ are unknown. It is easily verified that the proposed inverse problem is nonlinear. To our best knowledge, the inverse problem is new to the literature and the corresponding study becomes radically much more challenging. According to our earlier discussion, it would be of practical interest in EEG and MEG if one intends to infer knowledge on both the brain activity and the brain tissue and then study their correlations, by exterior EM measurements. In the current article, we shall be mainly concerned with the theoretical identifiability results for the inverse problem (1.3); namely, (1.4). That is, given the measurement data set $\Pi_{\mathcal{J}, \epsilon, \mu, \sigma}$, we aim to establish sufficient conditions for $\mathcal{J}$ and $(B; \epsilon, \mu, \sigma)$ such that both of them can be identified. Generically speaking, if the medium parameters are piecewise constants and the source current is invariant along any given fixed direction, then we show that all of them can be recovered. To our best knowledge these identifiability results are new. Besides the basic identifiability results our results points give possible directions on recovering more general unknowns by either approximating them with the ones that can be identified, or by devising different measurement methods.

Another practical scenario that is related to our proposed study is the thermoacoustic and photoacoustic tomography [13, 17–19], where one intends to infer knowledge of an inside body by exterior acoustic wave measurement that is generated by an internal source. In particular, in our recent paper [13], the simultaneous recovery of an internal source and the sound speed of the surrounding medium in thermoacoustic and photoacoustic tomography was considered, when the governing PDE is the scalar wave equation. For the proposed inverse problem (1.3) associated with the Maxwell system (1.1), one would encounter much more complicated analysis and technical difficulties in establishing the corresponding identifiability results than those in [13].

1.3. Some remarks. Before beginning with the mathematical study, some general remarks are in order. The major findings in this paper are contained in Theorems 3.1 and 3.2. Generically speaking, if the source term $\mathcal{J}(\mathbf{x}, t) = \mathbf{J}(\mathbf{x})\delta(t)$ with $\mathbf{J}$ invariant along any given direction or a harmonic function, and the medium $(B; \epsilon, \mu, \sigma)$ possesses material parameters being piecewise constants, then one can recover both the source and the medium. We would like to remark that our simultaneous recovery results may not be exclusive, and the unique recovery might hold for other scenarios. The main mathematical arguments to establish the recovery result are first to reduce the Maxwell system (1.1) from the time domain to the frequency domain and then to derive integral representations of the electric and magnetic fields, respectively. Next by doing asymptotic analysis in the low frequency

regime, we can derive integral identities involving the source function and the material parameters, which are coupled together. By inverting those integral identities using harmonic analysis techniques, we obtain the desired unique recovery results.

In Section 2, we present some results concerning the forward Maxwell system (1.1), especially the integral representations and the asymptotic expansions of the solutions with respect to the frequency ω . Section 3 is devoted to the unique recovery results.

2. AUXILIARY RESULTS ON THE FORWARD MAXWELL SYSTEM

2.1. The time-harmonic Maxwell system. By using standard Fourier analysis techniques, we will consider the problem in the frequency domain as described in what follows (cf. [8, 14]). Set

$$\mathcal{E}(\mathbf{x}, t) = \Re \mathbf{E}(\mathbf{x}; \omega) e^{i\omega t}, \quad \mathcal{H}(\mathbf{x}, t) = \Re \mathbf{H}(\mathbf{x}; \omega) e^{i\omega t}, \quad (2.1)$$

and

$$\mathcal{J}(\mathbf{x}, t) = \mathbf{J}(\mathbf{x}) \delta(t), \quad (2.2)$$

where $\omega \in \mathbb{R}_+$ is known as a *frequency*. By plugging (2.1) and (2.2) into (1.1), we have the following reduced time-harmonic Maxwell system

$$\begin{cases} \nabla \times \mathbf{E} - i\omega\mu\mathbf{H} = 0 & \text{in } \mathbb{R}^3, \\ \nabla \times \mathbf{H} + i\omega(\epsilon + i\frac{\sigma}{\omega})\mathbf{E} = \mathbf{J} & \text{in } \mathbb{R}^3, \end{cases} \quad (2.3)$$

subject to the Silver-Müller radiation condition:

$$\lim_{\|\mathbf{x}\| \rightarrow \infty} \|\mathbf{x}\| (\mathbf{H} \times \hat{\mathbf{x}} - \mathbf{E}) = 0, \quad (2.4)$$

where $\hat{\mathbf{x}} = \mathbf{x}/\|\mathbf{x}\|$ for $\mathbf{x} \in \mathbb{R}^3 \setminus \{0\}$. In what follows, if $\mathbf{E}$ and $\mathbf{H}$ satisfy (2.4), they will be referred to as radiating fields.

In order to provide a functional analysis framework for our investigation of (2.3), we next introduce some Sobolev spaces (cf. [12, 14]). In what follows, we shall often use the spaces

$$H_{loc}(\text{curl}; X) = \{\mathbf{U}|_D \in H(\text{curl}; D); D \text{ is any bounded subdomain of } X\}$$

and

$$H(\text{curl}; D) = \{\mathbf{U} \in (L^2(D))^3; \nabla \times \mathbf{U} \in (L^2(D))^3\}.$$

We also define the following spaces

$$H_{loc}(\text{div}; X) = \{\mathbf{U}|_D \in H(\text{div}; D); D \text{ is any bounded subdomain of } X\}$$

and

$$H(\text{div}; D) = \{\mathbf{U} \in (L^2(D))^3; \nabla \cdot \mathbf{U} \in (L^2(D))^3\}.$$

Furthermore, for $\beta \in L^\infty(D)$, we denote by $H(\text{div}(\beta \cdot); D)$ the function space

$$H(\text{div}(\beta \cdot); D) = \{\mathbf{U}|_D \in (L^2(D))^3; \nabla \cdot (\beta \mathbf{U}) \in (L^2(D))^3\}$$

We suppose in the sequel that $\mathbf{J} \in H_0(\text{div}; B)$, where $H_0(\text{div}; B)$ stands for all the functions which are in $H(\text{div}; B)$ and compactly supported

in B . We define similarly for space $H_0(\text{curl}; B)$. It is also assumed that ϵ, μ and σ belong to $L^\infty(\mathbb{R}^3)$. It is recalled that

$$\epsilon = \epsilon_0, \quad \mu = \mu_0, \quad \mathbf{J} = 0 \quad \text{and} \quad \sigma = 0, \quad \text{in} \quad \mathbb{R}^3 \setminus \overline{B}, \quad (2.5)$$

We refer to [12] for the unique existence of solutions $\mathbf{E}, \mathbf{H} \in H_{loc}(\text{curl}; \mathbb{R}^3)$ to the Maxwell system (2.3). It is readily seen that $\mathbf{E} \in H_{loc}(\text{curl}; \mathbb{R}^3) \cap H(\text{div}(\epsilon \cdot); \mathbb{R}^3)$ and $\mathbf{H} \in H_{loc}(\text{curl}; \mathbb{R}^3) \cap H(\text{div}(\mu \cdot); \mathbb{R}^3)$.

With the above preparations, the inverse problem (1.3) can be reformulated in the frequency domain associated with the reduced Maxwell system (2.3) as

$$\Pi_{\mathbf{J}, \epsilon, \mu, \sigma}(\mathbf{x}, \omega) \rightarrow (B; \mathbf{J}, \epsilon, \mu, \sigma). \quad (2.6)$$

where

$$\Pi_{\mathbf{J}, \epsilon, \mu, \sigma}(\mathbf{x}, \omega) = (\mathbf{E}, \mathbf{H})(\mathbf{x}; \omega)|_{(\mathbf{x}, \omega) \in \partial B \times \mathbb{R}_+}. \quad (2.7)$$

We would like to point out that as part of our results on the inverse problem (2.6), if μ is known, then it is sufficient to make use of the measurements of the electric field $\mathbf{E}$. Similarly, if ϵ is known, then it is enough to make use of the measurements of the magnetic field $\mathbf{H}$; see our main recovery results in Theorem 3.1. Furthermore, in all cases, we shall actually only make use of the frequency ω in a neighborhood of the zero frequency.

2.2. Integral representations. In this subsection, for the subsequent use, we present the integral representations of the electric field $\mathbf{E}$ and magnetic field $\mathbf{H}$ to the Maxwell system (2.3). Our discussion follows the general treatment in [14].

Define $k_0 := \omega \sqrt{\epsilon_0 \mu_0}$ to be the wave number. Let Γ_{k_0} be the outgoing fundamental solution to the PDO $-(\Delta + k_0^2)$, that is given by

$$\Gamma_{k_0}(\mathbf{x}) = \frac{e^{ik_0 \|\mathbf{x}\|}}{4\pi \|\mathbf{x}\|}. \quad (2.8)$$

For any bounded domain $B \subset \mathbb{R}^3$, denote by $\mathcal{V}_B^{k_0} : L_{loc}^2(B)^3 \rightarrow L_{loc}^2(B)^3$ the volume potential operator defined by

$$\mathcal{V}_B^{k_0}[\Phi](\mathbf{x}) := \int_B \Gamma_{k_0}(\mathbf{x} - \mathbf{y}) \Phi(\mathbf{y}) d\mathbf{y}. \quad (2.9)$$

We also denote by $\mathcal{S}_B^{k_0} : H^{-1/2}(\partial B) \rightarrow H^{1/2}(\partial B)$ the single layer potential operator given by

$$\mathcal{S}_B^{k_0}[\phi](\mathbf{x}) := \int_{\partial B} \Gamma_{k_0}(\mathbf{x} - \mathbf{y}) \phi(\mathbf{y}) ds_{\mathbf{y}}, \quad (2.10)$$

and $\mathcal{K}_B^{k_0} : H^{-1/2}(\partial B) \rightarrow H^{1/2}(\partial B)$ the Neumann-Poincaré operator

$$\mathcal{K}_B^{k_0}[\phi](\mathbf{x}) := \text{p.v.} \int_{\partial B} \frac{\partial \Gamma_{k_0}(\mathbf{x} - \mathbf{y})}{\partial \nu_y} \phi(\mathbf{y}) ds_{\mathbf{y}}, \quad (2.11)$$

where p.v. stands for the Cauchy principle value. In (2.11) and also in what follows, ν denotes the exterior unit normal vector to the boundary

of the domain concerned. It is known that the single layer potential operator $\mathcal{S}_B^{k_0}$ satisfies the trace formula

$$\frac{\partial}{\partial \nu} \mathcal{S}_B^{k_0}[\phi] \Big|_{\pm} = (\pm \frac{1}{2}I + (\mathcal{K}_B^{k_0})^*)[\phi] \quad \text{on } \partial B, \quad (2.12)$$

where $(\mathcal{K}_B^{k_0})^*$ is the adjoint operator of $\mathcal{K}_B^{k_0}$.

Define a 6×6 matrix operator $\mathbf{G}$ as follows,

$$\mathbf{G}(\mathbf{x}) = \begin{pmatrix} (k_0^2 I_3 + D^2) \Gamma_{k_0}(\mathbf{x}) & i\omega \mu_0 \nabla \times (\Gamma_{k_0}(\mathbf{x}) I_3) \\ -i\omega \epsilon_0 \nabla \times (\Gamma_{k_0}(\mathbf{x}) I_3) & (k_0^2 I_3 + D^2) \Gamma_{k_0}(\mathbf{x}) \end{pmatrix}, \quad (2.13)$$

where and also in what follows, I_n is the $n \times n$ identity matrix and D^2 stands for the double differentiation ∇^2 . Then the solution to (2.3) and (2.4) can be represented by

$$\begin{pmatrix} \mathbf{E} \\ \mathbf{H} \end{pmatrix} = \int_{\mathbb{R}^3} \mathbf{G}(\cdot - \mathbf{y}) \begin{pmatrix} \tilde{\gamma}(\mathbf{y}) \mathbf{E}(\mathbf{y}) + i/(\omega \epsilon_0) \mathbf{J}(\mathbf{y}) \\ \tilde{\mu}(\mathbf{y}) \mathbf{H}(\mathbf{y}) \end{pmatrix} d\mathbf{y}, \quad (2.14)$$

where and also in what follows,

$$\tilde{\gamma} := (\epsilon + i\sigma/\omega - \epsilon_0)/\epsilon_0 \quad \text{and} \quad \tilde{\mu} := (\mu - \mu_0)/\mu_0. \quad (2.15)$$

It can be readily seen from (2.14) that $\mathbf{E}(\mathbf{x}) = \mathcal{O}(\|\mathbf{x}\|^{-1})$, $\mathbf{H}(\mathbf{x}) = \mathcal{O}(\|\mathbf{x}\|^{-1})$ as $\|\mathbf{x}\| \rightarrow +\infty$.

One can rewrite (2.14) as

$$\begin{aligned} \mathbf{E} &= (k_0^2 I_3 + D^2) \int_{\mathbb{R}^3} \Gamma_{k_0}(\mathbf{x} - \mathbf{y}) (\tilde{\gamma} \mathbf{E} + i/(\omega \epsilon_0) \mathbf{J})(\mathbf{y}) d\mathbf{y} \\ &\quad + i\omega \mu_0 \nabla \times \int_{\mathbb{R}^3} \Gamma_{k_0}(\mathbf{x} - \mathbf{y}) \tilde{\mu}(\mathbf{y}) \mathbf{H}(\mathbf{y}) d\mathbf{y}, \\ \mathbf{H} &= -i\omega \epsilon_0 \nabla \times \int_{\mathbb{R}^3} \Gamma_{k_0}(\mathbf{x} - \mathbf{y}) (\tilde{\gamma} \mathbf{E} + i/(\omega \epsilon_0) \mathbf{J})(\mathbf{y}) d\mathbf{y} \\ &\quad + (k_0^2 I_3 + D^2) \int_{\mathbb{R}^3} \Gamma_{k_0}(\mathbf{x} - \mathbf{y}) \tilde{\mu}(\mathbf{y}) \mathbf{H}(\mathbf{y}) d\mathbf{y}. \end{aligned} \quad (2.16)$$

By virtue of (2.16), along with straightforward calculations, we can further show that

$$\begin{pmatrix} \omega \mathbf{E} \\ \mathbf{H} \end{pmatrix} = \mathcal{M}_B^{k_0} \begin{pmatrix} \tilde{\gamma} \omega \mathbf{E} \\ \tilde{\mu} \mathbf{H} \end{pmatrix} + \begin{pmatrix} i/\epsilon_0 (k_0^2 I_3 + D^2) \mathcal{V}_B^{k_0}[\mathbf{J}] \\ \nabla \times \mathcal{V}_B^{k_0}[\mathbf{J}] \end{pmatrix} \quad \text{in } \mathbb{R}^3, \quad (2.17)$$

where the operator $\mathcal{M}_B^{k_0}$ is defined by

$$\mathcal{M}_B^{k_0} := \begin{pmatrix} (k_0^2 I_3 + D^2) \mathcal{V}_B^{k_0} & i\omega^2 \mu_0 \nabla \times \mathcal{V}_B^{k_0} \\ -i\epsilon_0 \nabla \times \mathcal{V}_B^{k_0} & (k_0^2 I_3 + D^2) \mathcal{V}_B^{k_0} \end{pmatrix}. \quad (2.18)$$

We mention that the notation $D^2 \mathcal{V}_B^{k_0}$ appearing in (2.17) and (2.18) stands for $\nabla(\nabla \cdot \mathcal{V}_B^{k_0})$, and we shall also make use of such a notation in what follows.

2.3. Asymptotic expansions. By using the integral representation (2.17), we next derive the asymptotic expansions of $\mathbf{E}$ and $\mathbf{H}$ as $\omega \rightarrow +0$. To that end, we first derive an important lemma. In the following, if $k_0 = 0$, we formally set Γ_{k_0} introduced in (2.8) to be $\Gamma_0 = 1/(4\pi\|\mathbf{x}\|)$, and the other integral operators introduced in the previous subsection can also be formally defined when $k_0 = 0$.

Lemma 2.1. *The operator $D^2\mathcal{V}_B^0$ is a semi-negative definite operator which maps $H_0(\text{div}; B)$ to $H^1(B)^3$. Furthermore, the only possible eigenvalue of $D^2\mathcal{V}_B^0$ in $H_0(\text{div}; B)$ is -1 and the corresponding eigenfunction Φ is in $H^1(B)^3$ satisfies*

$$D^2\mathcal{V}_B^0[\Phi] = -\Phi, \quad \nabla \cdot \Phi \neq 0 \quad \text{and} \quad \nabla \times \Phi = 0. \quad (2.19)$$

If $\Phi \in H_0(\text{div}; B)$ and $\nabla \cdot \Phi = 0$ then

$$D^2\mathcal{V}_B^0[\Phi] = 0. \quad (2.20)$$

Proof. First, let $\Phi \in H_0(\text{div}; B)$, by using the identity $\partial\Gamma_{k_0}(\mathbf{x}-\mathbf{y})/\partial\mathbf{x}_i = -\partial\Gamma_{k_0}(\mathbf{x}-\mathbf{y})/\partial\mathbf{y}_i$ and integration by parts, we have

$$\begin{aligned} D^2\mathcal{V}_B^0[\Phi](\mathbf{x}) &= \nabla \nabla \cdot \int_B \Gamma_0(\mathbf{x}-\mathbf{y})\Phi(\mathbf{y})d\mathbf{y} \\ &= \nabla \int_B \Gamma_0(\mathbf{x}-\mathbf{y})(\nabla \cdot \Phi)(\mathbf{y})d\mathbf{y} = \nabla \mathcal{V}_B^0[\nabla \cdot \Phi]. \end{aligned} \quad (2.21)$$

By using the fact that $\mathcal{V}_B^0$ maps $L^2(B)$ to $H^2(B)$ (cf. [8]), we can easily see that $D^2\mathcal{V}_B^0[\Phi] \in H^1(B)^3$. If $\Phi \in H_0(\text{div}; B)$ and $\nabla \cdot \Phi = 0$ then by using (2.21), we prove (2.20).

Next for $\Phi \in H_0(\text{div}; B)$ and $\nabla \cdot \Phi \neq 0$, by integration by parts, one can show

$$\begin{aligned} \langle D^2\mathcal{V}_B^0[\Phi], \Phi \rangle &= \int_B D^2\mathcal{V}_B^0[\Phi] \cdot \Phi = - \int_B \mathcal{V}_B^0[\nabla \cdot \Phi] \nabla \cdot \Phi \\ &= \int_B \mathcal{V}_B^0[\nabla \cdot \Phi] \Delta(\mathcal{V}_B^0[\nabla \cdot \Phi]) \\ &= - \int_B \|\nabla \mathcal{V}_B^0[\nabla \cdot \Phi]\|^2 \leq 0, \end{aligned}$$

which proves that $D^2\mathcal{V}_B^0$ is semi-negative definite on $H_0(\text{div}; B)$.

Finally, suppose $\lambda \neq 0$ is a possible eigenvalue of $D^2\mathcal{V}_B^0$ in $H_0(\text{div}; B)$, we have

$$D^2\mathcal{V}_B^0[\Phi] = \lambda\Phi, \quad \Phi \in H_0(\text{div}; B),$$

which implies that Φ is also in $H_0(\text{curl}; B)$. By taking respectively curl and divergence of both sides of the above equation, we obtain

$$0 = \lambda \nabla \times \Phi, \quad -\nabla \cdot \Phi = \lambda \nabla \cdot \Phi,$$

which proves (2.19).

The proof is complete. $\square$

We proceed with the asymptotic analysis as $\omega \rightarrow +0$.

Proposition 2.1. *From (2.17), one can show that*

$$\mathcal{A}_B^{k_0} \begin{pmatrix} \omega \mathbf{E} \\ \mathbf{H} \end{pmatrix} = \begin{pmatrix} i/\epsilon_0(k_0^2 I_3 + D^2) \mathcal{V}_B^{k_0}[\mathbf{J}] \\ \nabla \times \mathcal{V}_B^{k_0}[\mathbf{J}] \end{pmatrix} \quad \text{in } \mathbb{R}^3, \quad (2.22)$$

where $\mathcal{A}_B^{k_0}$ is defined by

$$\mathcal{A}_B^{k_0} := I_6 - \mathcal{M}_B^{k_0} \begin{pmatrix} \tilde{\gamma} & 0 \\ 0 & \tilde{\mu} \end{pmatrix}. \quad (2.23)$$

For $\omega > 0$ sufficiently small, we have the following asymptotic expansions of $\mathcal{A}_B^{k_0}$ with respect to ω ,

$$\mathcal{A}_B^{k_0} = I_6 - \mathcal{M}_B^0 \begin{pmatrix} \tilde{\gamma} & 0 \\ 0 & \tilde{\mu} \end{pmatrix} + \omega^2 \mathcal{R}_B^{k_0}, \quad (2.24)$$

where $\mathcal{M}_B^0$ is defined by

$$\mathcal{M}_B^0 := \begin{pmatrix} D^2 \mathcal{V}_B^0 & 0 \\ -i\epsilon_0 \nabla \times \mathcal{V}_B^0 & D^2 \mathcal{V}_B^0 \end{pmatrix}, \quad (2.25)$$

and $\mathcal{R}_B^{k_0}$ is a remainder term. Furthermore, $\mathcal{R}_B^{k_0}$ is a bounded operator on $H_{loc}^2(\mathbb{R}^3)^3 \times H_{loc}^2(\mathbb{R}^3)^3$.

Proof. The proposition can be proved by straightforward calculations using (2.17) and (2.18). $\square$

In what follows, we introduce the following Sobolev space for $s \in \mathbb{R}$ and $|s| \leq 1/2$,

$$H_0^s(\partial B) = \{u \in H^s(\partial B); \int_{\partial B} u \, ds = 0\}. \quad (2.26)$$

For $\varepsilon \in L^\infty(B)$ and $\varepsilon > \alpha_0 \in \mathbb{R}_+$, we define

$$\Lambda_\varepsilon : H_0^{-1/2}(\partial B) \rightarrow H_0^{1/2}(\partial B)$$

to be the Neumann-to-Dirichlet map such that $\Lambda_\varepsilon[\varepsilon \partial u / \partial \nu|_{\partial B}] = u|_{\partial B}$, where $u \in H^1(B)$ is the solution to

$$\nabla \cdot \varepsilon \nabla u = 0 \quad \text{in } B \quad \text{and} \quad \int_{\partial B} u \, ds = 0.$$

It is remarked that Λ_ε is invertible. Define by $N_\varepsilon(\mathbf{x}, \mathbf{y})$ the Neumann function which satisfies

$$\begin{cases} \nabla \cdot \varepsilon \nabla N_\varepsilon(\cdot, \mathbf{y}) = -\delta_{\mathbf{y}}(\cdot) & \text{in } B, \\ \nu \cdot \varepsilon \nabla N_\varepsilon(\cdot, \mathbf{y})|_{\partial B} = -\frac{1}{|\partial B|}, \quad \int_{\partial B} N_\varepsilon(\mathbf{x}, \mathbf{y}) \, ds_{\mathbf{x}} = 0 & \text{for } \mathbf{y} \in B. \end{cases} \quad (2.27)$$

We shall also need the following assumption on the permittivity ϵ and conductivity σ

Assumption 1. Suppose that (ϵ, σ) satisfies one of the following two conditions

- (i) $\sigma = c\epsilon$ in B , where $c \geq 0$ is a constant;
- (ii) ϵ and σ are piecewise constants in $\mathbb{R}^3$ in the following sense. Set $\Sigma_0 := B$ and assume that Σ_j , $j = 1, 2, \dots, N$, are Lipschitz subdomains of Σ_0 such that $\Sigma_j \subseteq \Sigma_{j-1}$ and $\Sigma_{j-1} \setminus \overline{\Sigma_j}$ is connected for $1 \leq j \leq N$. Set $\epsilon^{(0)} = \epsilon_0$, $\sigma^{(0)} = 0$ and let $\epsilon^{(j)}$ and $\sigma^{(j)}$ be constants for $j = 1, 2, \dots, N+1$. The medium parameters are given as follows,

$$\begin{aligned}\epsilon &= \epsilon^{(0)} \chi(\mathbb{R}^3 \setminus \overline{\Sigma_0}) + \sum_{j=1}^N \epsilon^{(j)} \chi(\Sigma_{j-1} \setminus \overline{\Sigma_j}) + \epsilon^{(N+1)} \chi(\Sigma_N), \\ \sigma &= \sigma^{(0)} \chi(\mathbb{R}^3 \setminus \overline{\Sigma_0}) + \sum_{j=1}^N \sigma^{(j)} \chi(\Sigma_{j-1} \setminus \overline{\Sigma_j}) + \sigma^{(N+1)} \chi(\Sigma_N).\end{aligned}\tag{2.28}$$

In (2.28) and also in what follows, χ denotes the characteristic function.

With the above preparations at hand, we next show the following important lemma.

Lemma 2.2. *Let ϵ , μ and σ be those described in Section 1.1. Suppose further that σ and ϵ satisfy Assumption 1. Then there exists $\omega_0 \in \mathbb{R}_+$ such that for any $\omega \leq \omega_0$, (2.17) is uniquely solvable for $(\mathbf{E}, \mathbf{H}) \in H_{loc}(\text{curl}; \mathbb{R}^3) \times H_{loc}(\text{curl}; \mathbb{R}^3)$ and radiating at infinity. More specifically,*

$$\begin{pmatrix} \omega \mathbf{E} \\ \mathbf{H} \end{pmatrix} = (\mathcal{A}_B^0)^{-1} \begin{pmatrix} i/\epsilon_0 D^2 \mathcal{V}_B^0[\mathbf{J}] \\ \nabla \times \mathcal{V}_B^0[\mathbf{J}] \end{pmatrix} + \mathcal{O}(\omega^2) \quad \text{in } B, \tag{2.29}$$

where $(\mathcal{A}_B^0)^{-1}$ is given by

$$(\mathcal{A}_B^0)^{-1} = \begin{pmatrix} (I_3 - D^2 \mathcal{V}_B^0 \tilde{\gamma})^{-1} & 0 \\ -i\epsilon_0 (I_3 - D^2 \mathcal{V}_B^0 \tilde{\mu})^{-1} \nabla \times \mathcal{V}_B^0 (I_3 - D^2 \mathcal{V}_B^0 \tilde{\gamma})^{-1} & (I_3 - D^2 \mathcal{V}_B^0 \tilde{\mu})^{-1} \end{pmatrix}. \tag{2.30}$$

Proof. By direct computations, we first have the following asymptotic expansion for (2.22) (see (2.46) in what follows for the higher order expansion),

$$\mathcal{A}_B^{k_0} = \mathcal{A}_B^0 + \mathcal{O}(\omega^2), \tag{2.31}$$

where $\mathcal{A}_B^0$ stands for $\mathcal{A}_B^{k_0}$ with k_0 formally replaced by 0. In view of (2.22) and (2.31), it suffices to show that $\mathcal{A}_B^0$ is invertible and its inverse is given by (2.30). By (2.24), $\mathcal{A}_B^0$ can be represented by

$$\mathcal{A}_B^0 = I_6 - \mathcal{M}_B^0 \begin{pmatrix} \tilde{\gamma} & 0 \\ 0 & \tilde{\mu} \end{pmatrix}.$$

First, we consider the following equation

$$(I_3 - D^2 \mathcal{V}_B^0 \tilde{\gamma})[\omega \mathbf{E}] = i/\epsilon_0 D^2 \mathcal{V}_B^0[\mathbf{J}] \quad \text{in } \mathbb{R}^3 \tag{2.32}$$

with $\mathbf{E}$ radiating at infinity, then one has $\mathbf{E} \in H_{loc}(\text{curl}; \mathbb{R}^3)$ and satisfies

$$\nabla \times \mathbf{E} = 0, \quad \nabla \cdot ((1 + \tilde{\gamma})\omega \mathbf{E}) = i/\epsilon_0 \chi(B) \nabla \cdot \mathbf{J} \quad \text{in } \mathbb{R}^3.$$

Thus there exists $u \in H_{loc}^1(\mathbb{R}^3)$ such that $\mathbf{E} = \nabla u$ and

$$\nabla \cdot ((1 + \tilde{\gamma})\nabla u) = i\omega^{-1}\epsilon_0^{-1}\chi(B)\nabla \cdot \mathbf{J} \quad \text{in } \mathbb{R}^3, \quad (2.33)$$

where u is radiating at infinity.

By the condition (i) in Assumption 1 that $\sigma = c\epsilon$, one has $1 + \tilde{\gamma} = (1 + ci/\omega)\epsilon\epsilon_0^{-1}$ or equivalently,

$$\nabla \cdot (\epsilon \nabla u) = c_1(\omega)\chi(B)\nabla \cdot \mathbf{J} \quad \text{in } \mathbb{R}^3, \quad (2.34)$$

where $c_1(\omega) := i(\omega + ci)^{-1}$ and u is radiating at infinity. It is readily seen that the existence and uniqueness of a solution to (2.32) in $H_{loc}(\text{curl}; \mathbb{R}^3)$ is equivalent to the existence and uniqueness of a solution to (2.34) in $H_{loc}^1(\mathbb{R}^3)$. The uniqueness of the solution to (2.34) is known. In fact, it is equivalent to showing the unique trivial solution of the following equation

$$\begin{cases} \nabla \cdot \epsilon \nabla u = 0 & \text{in } B, \\ \Delta u = 0 & \text{in } \mathbb{R}^3 \setminus \overline{B}, \\ \frac{\partial u}{\partial \nu} \Big|_+ = \epsilon \frac{\partial u}{\partial \nu} \Big|_- & \text{on } \partial B, \\ u|_+ = u|_- & \text{on } \partial B, \\ u(x) = O(\|x\|^{-1}) & \text{as } \|x\| \rightarrow \infty, \end{cases}$$

which can be found in, e.g., [3]. For the existence of a solution to (2.34), we seek the solution in the following form

$$u(\mathbf{x}) = \begin{cases} \int_{\partial B} N_\epsilon(\mathbf{x}, \mathbf{y}) \psi(\mathbf{y}) ds_{\mathbf{y}} \\ -c_1(\omega) \int_B N_\epsilon(\mathbf{x}, \mathbf{y}) (\nabla \cdot \mathbf{J})(\mathbf{y}) d\mathbf{y} + C, & \mathbf{x} \in B, \\ \mathcal{S}_B^0[\phi](\mathbf{x}), & \mathbf{x} \in \mathbb{R}^3 \setminus B, \end{cases} \quad (2.35)$$

where $(\phi, \psi) \in H^{-1/2}(\partial B) \times H_0^{-1/2}(\partial B)$ and C is a constant that satisfies

$$C = \frac{1}{|\partial B|} \int_{\partial B} \mathcal{S}_B^0[\phi](\mathbf{x}) ds_{\mathbf{x}}.$$

By using the transmission conditions, which are implied in (2.34) and (2.35), ϕ and ψ satisfy the following system of integral equations on ∂B ,

$$\begin{cases} -\mathcal{S}_B^0[\phi] + \frac{1}{|\partial B|} \int_{\partial B} \mathcal{S}_B^0[\phi] + \Lambda_\epsilon[\psi] = c_1(\omega) \int_B N_\epsilon(\cdot, \mathbf{y}) (\nabla \cdot \mathbf{J})(\mathbf{y}) d\mathbf{y} \\ -(\frac{1}{2}I + (\mathcal{K}_B^0)^*)[\phi] + \psi = 0 \end{cases} \quad (2.36)$$

The unique solvability of (2.36) in $H^{-1/2}(\partial B) \times H_0^{-1/2}(\partial B)$ can be found in [2], noting that $\int_B N_\epsilon(\cdot, \mathbf{y})(\nabla \cdot \mathbf{J})(\mathbf{y}) d\mathbf{y}$ is in $H_0^{1/2}(\partial B)$. We have proved the unique solvability of (2.34), which in turn implies the unique solvability of (2.32).

We proceed to consider the other case that (ϵ, σ) fulfils (ii) in Assumption 1, namely, ϵ and σ are of the form specified in (2.28). Let

$$u = u^R + iu^I,$$

where u^R and u^I represent the real and imaginary parts of u , respectively. Then (2.33) can be expanded to the following equations

$$\begin{cases} \epsilon^{(j)} \Delta u^R - \sigma^{(j)} \omega^{-1} \Delta u^I = 0, & \text{in } \Sigma_{j-1} \setminus \overline{\Sigma_j}, \\ \epsilon^{(j)} \Delta u^I + \sigma^{(j)} \omega^{-1} \Delta u^R = \nabla \cdot \mathbf{J}, & \text{in } \Sigma_{j-1} \setminus \overline{\Sigma_j}, \\ \epsilon^{(N+1)} \Delta u^R - \sigma^{(N+1)} \omega^{-1} \Delta u^I = 0, & \text{in } \Sigma_N, \\ \epsilon^{(N+1)} \Delta u^I + \sigma^{(N+1)} \omega^{-1} \Delta u^R = \nabla \cdot \mathbf{J}. & \text{in } \Sigma_N, \end{cases} \quad (2.37)$$

where $j = 1, 2, \dots, N$. By (2.37), one can then obtain that

$$\Delta u = \left(\sum_{j=1}^N c_j \chi(\Sigma_{j-1} \setminus \overline{\Sigma_j}) + c_{N+1} \chi(\Sigma_N) \right) \nabla \cdot \mathbf{J} \quad (2.38)$$

holds in $\mathbb{R}^3$, where

$$c_j(\omega) = \frac{\sigma^{(j)} + i\epsilon^{(j)}\omega}{(\epsilon^{(j)})^2\omega^2 + (\sigma^{(j)})^2}, \quad j = 1, 2, \dots, N+1.$$

Together with the fact that u is radiating at infinity, it is straightforward to show that (2.38) has a unique solution.

Next, we consider the following equation

$$(I_3 - D^2 \mathcal{V}_B^0 \tilde{\mu})[\mathbf{H}] = \nabla \times \mathcal{V}_B^0[\mathbf{J}] \quad \text{in } \mathbb{R}^3 \quad (2.39)$$

where $\mathbf{H}$ is radiating at infinity, then one has $\mathbf{H} \in H_{loc}(\text{curl}; \mathbb{R}^3)$ and

$$\nabla \times (\mathbf{H} - \nabla \times \mathcal{V}_B^0[\mathbf{J}]) = 0, \quad \nabla \cdot ((1 + \tilde{\mu})\mathbf{H}) = 0, \quad \text{in } \mathbb{R}^3.$$

Noting that $1 + \tilde{\mu} = \mu$, there exists $u \in H_{loc}^1(\mathbb{R}^3)$ such that $\mathbf{H} = \nabla u + \nabla \times \mathcal{V}_B^0[\mathbf{J}]$ and

$$\nabla \cdot \mu \nabla u = -\nabla \cdot (\mu \nabla \times \mathcal{V}_B^0[\mathbf{J}]) \quad \text{in } \mathbb{R}^3. \quad (2.40)$$

Since $\nabla \cdot (\mu \nabla \times \mathcal{V}_B^0[\mathbf{J}]) = 0$ in $\mathbb{R}^3 \setminus \overline{B}$, one can prove similarly that (2.40) has a unique solution, and thus (2.39) has a unique solution.

Now, we consider the following more general case. Suppose $\mathbf{M} \in H_{loc}(\text{curl}; \mathbb{R}^3) \cap H_{loc}(\text{div}; \mathbb{R}^3)$ and $\varepsilon \in L^\infty(\mathbb{R}^3)$ and $\varepsilon = 0$ in $\mathbb{R}^3 \setminus \overline{B}$. Let $\mathbf{F}$ be in $H_{loc}(\text{curl}; \mathbb{R}^3) \cap H(\text{div}((1 + \varepsilon)\cdot); \mathbb{R}^3)$ and radiating at infinity. We prove that the following equation is uniquely solvable

$$(I_3 - D^2 \mathcal{V}_B^0 \varepsilon)[\mathbf{F}] = \mathbf{M}. \quad (2.41)$$

In fact, by taking curl and divergence of both sides of (2.41), respectively, one has

$$\nabla \times (\mathbf{F} - \mathbf{M}) = 0, \quad \nabla \cdot (1 + \varepsilon)\mathbf{F} = \nabla \cdot \mathbf{M}. \quad (2.42)$$

Then by (2.42) there exists $u \in H_{loc}^1(\mathbb{R}^3)$ such that $\mathbf{F} - \mathbf{M} = \nabla u$ and

$$\nabla \cdot (1 + \varepsilon) \nabla u = -\nabla \cdot (\varepsilon \mathbf{M}) \quad (2.43)$$

together with u radiating at infinity. Noting that $\nabla \cdot (\varepsilon \mathbf{M}) = 0$ in $\mathbb{R}^3 \setminus \overline{B}$, one can prove the unique solvability of (2.43) by using exactly the same method as that for (2.34) and (2.40).

To sum up, we can solve (2.22) as follows. From the first equation in (2.22) one can uniquely obtain

$$\omega \mathbf{E} = i/\epsilon_0 (I_3 - D^2 \mathcal{V}_B^0 \tilde{\gamma})^{-1} D^2 \mathcal{V}_B^0 [\mathbf{J}] + \mathcal{O}(\omega^2),$$

then by using the second equation, that is,

$$(I_3 - D^2 \mathcal{V}_B^0 \tilde{\mu})[\mathbf{H}] = -i\epsilon_0 \nabla \times \mathcal{V}_B^0 [\tilde{\gamma} \omega \mathbf{E}] + \nabla \times \mathcal{V}_B^0 [\mathbf{J}] + \mathcal{O}(\omega^2),$$

one can uniquely obtain that

$$\mathbf{H} = -i\epsilon_0 (I_3 - D^2 \mathcal{V}_B^0 \tilde{\gamma})^{-1} \nabla \times \mathcal{V}_B^0 [\tilde{\gamma} \omega \mathbf{E}] + (I_3 - D^2 \mathcal{V}_B^0 \tilde{\gamma})^{-1} \nabla \times \mathcal{V}_B^0 [\mathbf{J}] + \mathcal{O}(\omega^2).$$

Using the above facts, we can directly verify that $(\mathcal{A}_B^0)^{-1}$ is given in (2.30). Finally, (2.29) can be shown by straightforward asymptotic expansion with respect to ω .

The proof is complete. $\square$

In (2.29), we only derived the leading-order expansion of $[\omega \mathbf{E}, \mathbf{H}]$. In some cases in what follows, we shall also need the higher-order expansion of $[\omega \mathbf{E}, \mathbf{H}]$, which we shall give in what follows. Since the proof is completely similar to that of Lemma 2.2, we only sketch it. Suppose that ω is sufficiently small such that $\omega \|\mathbf{x}\| \ll 1$ for $\mathbf{x} \in B$, then there holds the following expansion for $\mathcal{M}_B^{k_0}$ in (2.18),

$$\mathcal{M}_B^{k_0} = \mathcal{M}_B^0 + k_0^2 \mathcal{M}_{B,1} + \mathcal{O}(\omega^3), \quad (2.44)$$

where $\mathcal{M}_B^0$ is defined in (2.25) and $\mathcal{M}_{B,1}$ is defined by

$$\mathcal{M}_{B,1} := \begin{pmatrix} \mathcal{V}_B^0 + D^2 \mathcal{L}_B & i/\epsilon_0 \nabla \times \mathcal{V}_B^0 \\ -i\epsilon_0 \nabla \times \mathcal{L}_B & \mathcal{V}_B^0 + D^2 \mathcal{L}_B \end{pmatrix},$$

with $\mathcal{L}_B$ given by

$$\mathcal{L}_B[\Phi] := -\frac{1}{4\pi} \int_B \|\mathbf{x} - \mathbf{y}\| \Phi(\mathbf{y}) d\mathbf{y}. \quad (2.45)$$

Then by definition (2.23) we have the following expansion for $\mathcal{A}_B^{k_0}$,

$$\mathcal{A}_B^{k_0} = \mathcal{A}_B^0 - k_0^2 \mathcal{M}_{B,1} \Upsilon + \mathcal{O}(\omega^3), \quad (2.46)$$

where Υ is defined by

$$\Upsilon := \begin{pmatrix} \tilde{\gamma} & 0 \\ 0 & \tilde{\mu} \end{pmatrix}, \quad (2.47)$$

and

$$\mathcal{A}_B^0 := I_6 - \mathcal{M}_B^0 \Upsilon.$$

With the above computations, we obtain

Theorem 2.1. *Suppose that ϵ, μ and σ are as in Lemma 2.2, and in particular note that ϵ and σ satisfy Assumption 1. Then there exists $\omega_0 \in \mathbb{R}_+$ such that for $\omega \leq \omega_0$, the solution to (2.3) and (2.4) admits the following asymptotic expansion in B ,*

$$\begin{aligned} \begin{pmatrix} \omega \mathbf{E} \\ \mathbf{H} \end{pmatrix} &= (\mathcal{A}_B^0)^{-1} \begin{pmatrix} i/\epsilon_0 D^2 \mathcal{V}_B^0[\mathbf{J}] \\ \nabla \times \mathcal{V}_B^0[\mathbf{J}] \end{pmatrix} + k_0^2 (\mathcal{A}_B^0)^{-1} \begin{pmatrix} i/\epsilon_0 (\mathcal{V}_B^0 + D^2 \mathcal{L}_B)[\mathbf{J}] \\ \nabla \times \mathcal{L}_B[\mathbf{J}] \end{pmatrix} \\ &\quad + k_0^2 (\mathcal{A}_B^0)^{-1} \mathcal{M}_{B,1} \Upsilon (\mathcal{A}_B^0)^{-1} \begin{pmatrix} i/\epsilon_0 D^2 \mathcal{V}_B^0[\mathbf{J}] \\ \nabla \times \mathcal{V}_B^0[\mathbf{J}] \end{pmatrix} + \mathcal{O}(\omega^4). \end{aligned} \quad (2.48)$$

Corollary 2.2. *Suppose that ϵ, μ and σ are those in Theorem 2.1, and particularly ϵ and σ satisfy Assumption 1. Then there exists $\omega_0 \in \mathbb{R}_+$ such that for $\omega \leq \omega_0$, the solution to (2.3) and (2.4) admits the following asymptotic expansions in B*

$$\omega \mathbf{E} = i/\epsilon_0 (I_3 - D^2 \mathcal{V}_B^0 \tilde{\gamma})^{-1} D^2 \mathcal{V}_B^0[\mathbf{J}] + \mathcal{O}(\omega^2), \quad (2.49)$$

and

$$\mathbf{H} = -i\omega\epsilon_0 (I_3 - D^2 \mathcal{V}_B^0 \tilde{\mu})^{-1} \nabla \times \mathcal{V}_B^0[\mathbf{E}] + (I_3 - D^2 \mathcal{V}_B^0 \tilde{\mu})^{-1} \nabla \times \mathcal{V}_B^0[\mathbf{J}] + \mathcal{O}(\omega^2). \quad (2.50)$$

Furthermore, if $\nabla \cdot \mathbf{J} = 0$, then we have the following asymptotic expansions in B ,

$$\begin{aligned} \mathbf{E} &= i\omega\mu_0 (I_3 - D^2 \mathcal{V}_B^0 \tilde{\gamma})^{-1} \nabla \times \mathcal{V}_B^0 \tilde{\mu} (I_3 - D^2 \mathcal{V}_B^0 \tilde{\mu})^{-1} \nabla \times \mathcal{V}_B^0[\mathbf{J}] \\ &\quad + i\omega\mu_0 (I_3 - D^2 \mathcal{V}_B^0 \tilde{\gamma})^{-1} (\mathcal{V}_B^0 + D^2 \mathcal{L}_B)[\mathbf{J}] + \mathcal{O}(\omega^3), \end{aligned} \quad (2.51)$$

and

$$\mathbf{H} = (I_3 - D^2 \mathcal{V}_B^0 \tilde{\mu})^{-1} \nabla \times \mathcal{V}_B^0[\mathbf{J}] + \mathcal{O}(\omega^2). \quad (2.52)$$

Proof. By using (2.30) and (2.48) one can readily show that (2.49) and (2.50) hold in B . If $\nabla \cdot \mathbf{J} = 0$, then $\mathbf{J} \in H_0(\text{div}; B)$ and by (2.20), one obtains $D^2 \mathcal{V}_B^0[\mathbf{J}] = 0$. Hence, by substituting (2.49) into (2.50), one can show that (2.52) holds in B . By using the higher order expansion in (2.48), we can show that (2.51) holds in B .

The proof is complete. $\square$

Remark 2.1. We shall make use of the four asymptotic expansions contained in Corollary 2.2 to recover the source $\mathbf{J}$ and the material parameters ϵ and μ as they are contained in the coefficients of the expansions. It is noted that those coefficients satisfy some integral identities, and the unknowns are coupled together in those identities. We would also like to point out that in we cannot have that $\nabla \cdot \mathbf{J} = 0$ and $\nabla \times \mathbf{J} = 0$ hold simultaneously. Indeed, noting that $\mathbf{J}$ is compactly supported in B , and if both $\nabla \cdot \mathbf{J} = 0$ and $\nabla \times \mathbf{J} = 0$, then we must have that $\mathbf{J} \equiv 0$ by integrating by parts. Using this fact, together with the fact that $\nabla \times \mathcal{V}_B^0[\mathbf{J}] = \mathcal{V}_B^0[\nabla \times \mathbf{J}]$, we can then assume that the leading-order term in (2.52) is not vanishing.

3. UNIQUE RECOVERY RESULTS ON THE INVERSE PROBLEM

In this section, we present the main unique recovery results for the inverse problem (2.6), which are contained in Theorems 3.1 and 3.2. We first derive three important auxiliary lemmas.

In the following and throughout the rest of the paper, for a bounded domain Ω and a distribution ψ , we use $\psi|_{\partial\Omega}^+$ and $\psi|_{\partial\Omega}^-$, respectively, to denote the traces of ψ on $\partial\Omega$ when one approaches $\partial\Omega$ from outside and inside of Ω . The first auxiliary result is given as follows.

Lemma 3.1. *Suppose that ϵ, μ and σ are similar to those described in Theorem 2.1, and particularly $\sigma = c\epsilon$ in B with $c \geq 0$ a constant. Also, suppose that $\mathbf{J} \in H_0(\text{div}; B)$, which satisfies (2.5). If $\nabla \cdot \mathbf{J} \neq 0$, then for $\omega \in \mathbb{R}_+$ sufficiently small, $\mathbf{E}$ can be represented by $\mathbf{E} = \nabla(u_1 + u_2) + \mathcal{O}(\omega)$ in B , where u_1 and u_2 satisfy*

$$\begin{aligned} u_1 &= \begin{cases} \int_{\partial B} N_\epsilon(\cdot, \mathbf{y})(\nu \cdot \epsilon \mathbf{E}|_{\partial B}^-)(\mathbf{y}) ds_{\mathbf{y}} & \text{in } B \\ -\mathcal{S}_B^0 \Lambda_1^{-1}(\Lambda_1 - \Lambda_\epsilon)[\nu \cdot \epsilon \mathbf{E}|_{\partial B}^-] + C_1 & \text{in } \mathbb{R}^3 \setminus \overline{B}, \end{cases} \\ u_2 &= \begin{cases} c_1(\omega) \int_B N_\epsilon(\cdot, \mathbf{y})(\nabla \cdot \mathbf{J})(\mathbf{y}) d\mathbf{y} & \text{in } B \\ c_1(\omega) \mathcal{S}_B^0 \Lambda_1^{-1} \left[\int_B N_\epsilon(\cdot, \mathbf{y})(\nabla \cdot \mathbf{J})(\mathbf{y}) d\mathbf{y} \right] + C_2 & \text{in } \mathbb{R}^3 \setminus \overline{B}, \end{cases} \end{aligned} \quad (3.1)$$

with C_1 and C_2 two constants, respectively, given by

$$C_1 = \frac{1}{|\partial B|} \int_{\partial B} \mathcal{S}_B^0 \Lambda_1^{-1}(\Lambda_1 - \Lambda_\epsilon)[\nu \cdot \epsilon \mathbf{E}|_{\partial B}^-](\mathbf{y}) ds_{\mathbf{y}},$$

and

$$C_2 = -\frac{c_1(\omega)}{|\partial B|} \int_{\partial B} \mathcal{S}_B^0 \Lambda_1^{-1} \left[\int_B N_\epsilon(\cdot, \mathbf{y})(\nabla \cdot \mathbf{J})(\mathbf{y}) d\mathbf{y} \right] (\mathbf{x}) ds_{\mathbf{x}},$$

and $c_1(\omega) = i\epsilon_0^{-1}(\omega + ci)^{-1}$. If $\nabla \cdot \mathbf{J} = 0$ then $\mathbf{H}$ can be represented as $(I_3 + D^2 \mathcal{V}_B^0)[\mathbf{H}] = -\mu_0^{-1} \nabla \mathcal{S}_B^0[(\nu \cdot \mu \mathbf{H})|_{\partial B}^-] + \mathcal{V}_B^0[\nabla \times \mathbf{J}] + \mathcal{O}(\omega^2)$ in B . (3.2)

Proof. Recall from (2.49) that $\mathbf{E} \in H(\text{curl}; B)$ and satisfies

$$(I_3 - D^2 \mathcal{V}_B^0 \tilde{\gamma})[\omega \mathbf{E}] = i\epsilon_0^{-1} D^2 \mathcal{V}_B^0[\mathbf{J}] + \mathcal{O}(\omega^2) \quad \text{in } B. \quad (3.3)$$

By taking curl of both sides of (3.3), one readily has that

$$\nabla \times \mathbf{E} = \mathcal{O}(\omega), \quad (3.4)$$

and noting that $\mathbf{J} \in H_0(\text{div}; B)$, together with taking div of both sides of (3.3), one also has that

$$\nabla \cdot (1 + \tilde{\gamma})\mathbf{E} = -i\omega^{-1}\epsilon_0^{-1}\nabla \cdot \mathbf{J} + \mathcal{O}(\omega). \quad (3.5)$$

Let u be the solution to

$$\begin{cases} \nabla \cdot (\epsilon \nabla u) = -c_1(\omega) \nabla \cdot \mathbf{J} & \text{in } B \\ \Delta u = 0 & \text{in } \mathbb{R}^3 \setminus \overline{B} \\ \frac{\partial u}{\partial \nu} \Big|_+ = \epsilon \frac{\partial u}{\partial \nu} \Big|_- & \text{on } \partial B \\ u|_+ = u|_- & \text{on } \partial B \\ u(x) = O(\|x\|^{-1}) & \text{as } \|x\| \rightarrow \infty \end{cases}, \quad (3.6)$$

where $c_1(\omega) = i\epsilon_0^{-1}(\omega + ci)^{-1}$. Noting that $\sigma = c\epsilon$ in B , and by combining (3.4), (3.5) and (3.6), we thus have $\mathbf{E} = \nabla u + \mathcal{O}(\omega)$. The solution u to (3.6) can be written as $u = u_1 + u_2$ (see, e.g. [2]), where

$$u_1(\mathbf{x}) = \begin{cases} \int_{\partial B} N_\epsilon(\mathbf{x}, \mathbf{y}) (\nu \cdot \epsilon \mathbf{E}|_{\partial B}^-)(\mathbf{y}) ds_{\mathbf{y}}, & \mathbf{x} \in B \\ -\mathcal{S}_B^0 \Lambda_1^{-1} (\Lambda_1 - \Lambda_\epsilon) [\nu \cdot \epsilon \mathbf{E}|_{\partial B}^-](\mathbf{x}) + C_1, & \mathbf{x} \in \mathbb{R}^3 \setminus \overline{B} \end{cases}, \quad (3.7)$$

and

$$u_2 = \begin{cases} c_1(\omega) \int_B N_\epsilon(\mathbf{x}, \mathbf{y}) (\nabla \cdot \mathbf{J})(\mathbf{y}) d\mathbf{y}, & \mathbf{x} \in B \\ c_1(\omega) \mathcal{S}_B^0 \Lambda_1^{-1} \left[\int_B N_\epsilon(\cdot, \mathbf{y}) (\nabla \cdot \mathbf{J})(\mathbf{y}) d\mathbf{y} \right](\mathbf{x}) + C_2, & \mathbf{x} \in \mathbb{R}^3 \setminus \overline{B} \end{cases}, \quad (3.8)$$

with C_1 and C_2 two constants, respectively, given by

$$C_1 = \frac{1}{|\partial B|} \int_{\partial B} \mathcal{S}_B^0 \Lambda_{\epsilon_0}^{-1} (\Lambda_{\epsilon_0} - \Lambda_\epsilon) [\nu \cdot \epsilon \mathbf{E}|_{\partial B}^-](\mathbf{y}) ds_{\mathbf{y}},$$

and

$$C_2 = -\frac{c_1(\omega)}{|\partial B|} \int_{\partial B} \mathcal{S}_B^0 \Lambda_{\epsilon_0}^{-1} \left[\int_B N_\epsilon(\cdot, \mathbf{y}) (\nabla \cdot \mathbf{J})(\mathbf{y}) d\mathbf{y} \right](\mathbf{x}) ds_{\mathbf{x}}.$$

Therefore, (3.1) is proved.

Next, if $\nabla \cdot \mathbf{J} = 0$, then by (2.52) we have

$$(I_3 + D^2 \mathcal{V}_B^0)[\mathbf{H}] = D^2 \mathcal{V}_B^0[(1 + \tilde{\mu})\mathbf{H}] + \nabla \times \mathcal{V}_B^0[\mathbf{J}] + \mathcal{O}(\omega^2). \quad (3.9)$$

It can be readily verified that

$$\nabla \cdot (1 + \tilde{\mu})\mathbf{H} = \mathcal{O}(\omega^2). \quad (3.10)$$

Noting that $1 + \tilde{\mu} = \mu/\mu_0$, by (3.9), (3.10) and integration by parts, we obtain

$$\begin{aligned} & (I_3 + D^2 \mathcal{V}_B^0)[\mathbf{H}] \\ &= -\mu_0^{-1} \nabla \int_B \nabla_y \Gamma_0(\cdot - \mathbf{y}) \cdot (\mu \mathbf{H})(\mathbf{y}) ds_{\mathbf{y}} + \mathcal{V}_B^0[\nabla \times \mathbf{J}] + \mathcal{O}(\omega^2) \\ &= -\mu_0^{-1} \nabla \int_B \nabla_y \cdot (\Gamma_0(\cdot - \mathbf{y}) (\mu \mathbf{H})(\mathbf{y})) ds_{\mathbf{y}} + \mathcal{V}_B^0[\nabla \times \mathbf{J}] + \mathcal{O}(\omega^2) \\ &= -\mu_0^{-1} \nabla \mathcal{S}_B^0[(\nu \cdot \mu \mathbf{H})|_{\partial B}^-] + \mathcal{V}_B^0[\nabla \times \mathbf{J}] + \mathcal{O}(\omega^2). \end{aligned}$$

The proof is complete. $\square$

Next, we present the second auxiliary result.

Lemma 3.2. *Let $N_\varepsilon(\mathbf{x}, \mathbf{y})$ be defined in (2.27), and suppose that ε is a given positive constant in B . Then there holds the following identity,*

$$\begin{aligned} & \left(-\frac{I}{2} + \mathcal{K}_B^0 \right) \left[\int_B N_\varepsilon(\cdot - \mathbf{y})(\nabla \cdot \mathbf{J})(\mathbf{y}) d\mathbf{y} \right] (\mathbf{x}) \\ &= \varepsilon^{-1} \int_B \Gamma_0(\mathbf{x} - \mathbf{y})(\nabla \cdot \mathbf{J})(\mathbf{y}) d\mathbf{y}, \quad \mathbf{x} \in \partial B. \end{aligned} \quad (3.11)$$

Proof. For any $g \in H^{-1/2}(\partial B)$, we let u be defined by

$$u(\mathbf{y}) := \int_{\partial B} \left(-\frac{I}{2} + \mathcal{K}_B^0 \right) [N_\varepsilon(\cdot, \mathbf{y})](\mathbf{x}) g(\mathbf{x}) ds_{\mathbf{x}}, \quad \mathbf{y} \in B.$$

Then we conclude

$$u(\mathbf{y}) := \int_{\partial B} N_\varepsilon(\mathbf{x}, \mathbf{y}) \left(-\frac{I}{2} + (\mathcal{K}_B^0)^* \right) [g](\mathbf{x}) ds_{\mathbf{x}}, \quad \mathbf{y} \in B.$$

Noticing that ε is a constant, we have $\Delta u = 0$ and

$$\nu \cdot \nabla u = \varepsilon^{-1} \left(-\frac{I}{2} + (\mathcal{K}_B^0)^* \right) [g], \quad \int_{\partial B} u = 0, \quad \text{on } \partial B.$$

It is easily seen that u can also be represented by the formula

$$u = \varepsilon^{-1} \mathcal{S}_B^0[g] - \varepsilon^{-1} \int_{\partial B} \mathcal{S}_B^0[g](\mathbf{x}) ds_{\mathbf{x}}.$$

By using that $\int_B \nabla \cdot \mathbf{J} = 0$ we thus have

$$\begin{aligned} & \int_B \int_{\partial B} \left(-\frac{I}{2} + \mathcal{K}_B^0 \right) [N_\varepsilon(\cdot, \mathbf{y})](\mathbf{x}) g(\mathbf{x}) ds_{\mathbf{x}} (\nabla \cdot \mathbf{J})(\mathbf{y}) d\mathbf{y} \\ &= \varepsilon^{-1} \int_B \mathcal{S}_B^0[g](\mathbf{y}) (\nabla \cdot \mathbf{J})(\mathbf{y}) d\mathbf{y}. \end{aligned}$$

Finally, by interchanging the order of integrations and using the fact that $g \in H^{-1/2}(\partial B)$ is arbitrary, we readily have (3.11).

The proof is complete. $\square$

Remark 3.1. It is remarked that Lemma 3.2 is adapted and modified from Lemma 2.28 in [3]. Here for the sake of convenience to the readers and self-containedness of the paper, we present its proof.

Next we introduce two definitions.

Definition 3.1. We call a harmonic function u in B a *Herglotz harmonic function* with $\xi \in \mathbb{C}^3$ if

$$u(\mathbf{x}) = \alpha e^{i\mathbf{x} \cdot \xi} + \beta, \quad \mathbf{x} \in B, \quad (3.12)$$

where $\xi \neq \mathbf{0}$, $\xi \cdot \xi = 0$ and $\alpha, \beta \in \mathbb{C}$ are two constants.

Definition 3.2. We call a function $\Phi \in H^1(B)$ *admissible*, if one of the following two conditions is fulfilled:

- (i) $\Phi(x) = h(x)$ for $x \in B$, and h is a harmonic function in $\mathbb{R}^3$;

(ii) There exists a unit vector $\mathbf{d} \in \mathbb{S}^2$ such that $\mathbf{d} \cdot \nabla \Phi = 0$.

The following lemma shall also be needed.

Lemma 3.3. *Let $(\mathbf{E}, \mathbf{H})$ be the solution to (2.3) and (2.4). Suppose that (ϵ, μ, σ) and $\mathbf{J} \in H_0(\text{div}; B)$ satisfies (2.5) and $\nabla \cdot \mathbf{J} = 0$. Suppose further that ϵ and σ are piecewise constants in B which satisfy (2.28) in Assumption 1. Then there holds the following transmission condition,*

$$\nu \cdot (\epsilon^{(j)} + i\sigma^{(j)}/\omega)\mathbf{E}|_+ = \nu \cdot (\epsilon^{(j+1)} + i\sigma^{(j+1)}/\omega)\mathbf{E}|_- \quad \text{on } \partial\Sigma_j, \quad (3.13)$$

for $j = 0, 1, \dots, N$. Moreover, there also holds

$$\nu \cdot \mu_0 \mathbf{H}|_+ = \nu \cdot \mu \mathbf{H}|_- \quad \text{on } \partial B. \quad (3.14)$$

Proof. We only prove (3.13), and (3.14) can be proved by using similar arguments. By taking the divergence of both sides of the second equation in (2.3) and noting that $\nabla \cdot \mathbf{J} = 0$ by the assumption, we have

$$\nabla \cdot (\epsilon + i\sigma/\omega)\mathbf{E} = \nabla \cdot \mathbf{J} = 0 \quad \text{in } \mathbb{R}^3. \quad (3.15)$$

By taking the inner product of both sides of the second equation in (2.3) with the gradient of a test function $\psi \in C_0^\infty(\mathbb{R}^3)$, and integrating both sides over $\mathbb{R}^3$, there holds

$$\int_{\mathbb{R}^3} (\nabla \times \mathbf{H}) \cdot \nabla \psi = -i\omega \int_{\mathbb{R}^3} (\epsilon + i\sigma/\omega)\mathbf{E} \cdot \nabla \psi + \int_{\mathbb{R}^3} \mathbf{J} \cdot \nabla \psi. \quad (3.16)$$

By using a vector calculus identity and Green's formula, the LHS of (3.16) can be rewritten

$$\int_{\mathbb{R}^3} (\nabla \times \mathbf{H}) \cdot \nabla \psi = \int_{\mathbb{R}^3} \nabla \cdot (\mathbf{H} \times \nabla \psi) = 0. \quad (3.17)$$

By using (3.15) and Green's formula, the RHS of (3.16) implies

$$\begin{aligned} & -i\omega \int_{\mathbb{R}^3} (\epsilon + i\sigma/\omega)\mathbf{E} \cdot \nabla \psi + \int_{\mathbb{R}^3} \mathbf{J} \cdot \nabla \psi \\ &= -i\omega \int_{\mathbb{R}^3 \setminus \overline{\Sigma_j}} (\epsilon + i\sigma/\omega)\mathbf{E} \cdot \nabla \psi - i\omega \int_{\Sigma_j} (\epsilon + i\sigma/\omega)\mathbf{E} \cdot \nabla \psi \\ &= i\omega \int_{\partial\Sigma_j} \nu \cdot (\epsilon + i\sigma/\omega)\mathbf{E}|_+ \psi - i\omega \int_{\partial\Sigma_j} \nu \cdot (\epsilon + i\sigma/\omega)\mathbf{E}|_- \psi. \end{aligned} \quad (3.18)$$

By substituting (3.17) and (3.18) into (3.16), we get

$$\int_{\partial\Sigma_j} \nu \cdot (\epsilon + i\sigma/\omega)\mathbf{E}|_+ \psi = \int_{\partial\Sigma_j} \nu \cdot (\epsilon + i\sigma/\omega)\mathbf{E}|_- \psi. \quad (3.19)$$

Finally, since ψ is arbitrarily given, we thus have (3.13), which completes the proof. $\square$

We are ready to present the first main theorem that contains the results on the simultaneous recovery of ϵ, μ, σ and $\mathbf{J}$ from the knowledge of $\Pi_{\epsilon, \mu, \sigma, \mathbf{J}}$.

Theorem 3.1. *Let $(\epsilon_1, \mu_1, \sigma_1, \mathbf{J}_1)$ and $(\epsilon_2, \mu_2, \sigma_2, \mathbf{J}_2)$ be two sets of permittivity, permeability, conductivity and source current. Suppose $\epsilon_j > 0$, $\mu_j > 0$, $\mathbf{J}_j \in H_0(\text{div}; B)$, and $\sigma_j = c\epsilon_j$, where $c \geq 0$, $j = 1, 2$, which verify (2.5). Suppose further that ϵ_j, μ_j and σ_j are constants in B . Let $(\mathbf{E}_1, \mathbf{H}_1)$ and $(\mathbf{E}_2, \mathbf{H}_2)$ be the corresponding solutions to (2.3) and (2.4), associated with $(\epsilon_1, \mu_1, \sigma_1, \mathbf{J}_1)$ and $(\epsilon_2, \mu_2, \sigma_2, \mathbf{J}_2)$, respectively. If*

$$\Pi_{\epsilon_1, \mu_1, \sigma_1, \mathbf{J}_1}(\mathbf{x}, \omega) = \Pi_{\epsilon_2, \mu_2, \sigma_2, \mathbf{J}_2}(\mathbf{x}, \omega), \quad (\mathbf{x}, \omega) \in \partial B \times (0, \omega_0), \quad (3.20)$$

where ω_0 is any given positive constant, then we have the following results:

(i) Set $\Phi := \nabla \cdot (\mathbf{J}_1 - \mathbf{J}_2)$. If $\nabla \cdot \mathbf{J}_j \neq 0$ and

$$\nu \cdot \mathbf{H}_j|_{\partial B}^+ + \nu \cdot \mathbf{H}_j|_{\partial B}^+ \omega^{-1} \neq 0 \quad \text{as } \omega \rightarrow +0, \quad (3.21)$$

$j = 1, 2$, and $\epsilon_1 = \epsilon_2$, then $\Phi = 0$ if Φ satisfies the admissibility condition in Definition 3.2. Furthermore, if $\nabla \times \mathbf{J}_1 = \nabla \times \mathbf{J}_2 = 0$, then $\mathbf{J}_1 = \mathbf{J}_2$ and $\mu_1 = \mu_2$.

(ii) If $\nabla \cdot \mathbf{J}_j = 0$, and $\mathcal{S}_B^0[\nu \cdot \mathbf{H}_j|_{\partial B}^-]$ are some Herglotz harmonic function with ξ , and

$$\nu \cdot \mathbf{E}_j|_{\partial B}^+ + \nu \cdot \mathbf{E}_j|_{\partial B}^+ \omega^{-1} + \nu \cdot \mathbf{E}_j|_{\partial B}^+ \omega^{-2} \neq 0 \quad \text{as } \omega \rightarrow +0, \quad (3.22)$$

$j = 1, 2$, then we get that $\mathbf{J}_1 = \mathbf{J}_2$, $\mu_1 = \mu_2$ and $\epsilon_1 = \epsilon_2$ provided $\Phi := \xi \cdot (\nabla \times (\mathbf{J}_1 - \mathbf{J}_2))$ satisfies the admissibility condition in Definition 3.2.

Proof. We first prove case (i). Since ϵ_j , $j = 1, 2$ are constants in B , and $\nabla \cdot \mathbf{J}_j \neq 0$, $j = 1, 2$, by using (3.20), or $\nu \cdot \epsilon_1 \mathbf{E}_1 = \nu \cdot \epsilon_2 \mathbf{E}_2$ (see (3.14) and note that $\sigma_j = c\epsilon_j$) on ∂B , the first line in (3.7), (3.8), (2.27) and $\epsilon_1 = \epsilon_2$, we have

$$\int_B N_{\epsilon_1}(\mathbf{x}, \mathbf{y})(\nabla \cdot (\mathbf{J}_1 - \mathbf{J}_2))(\mathbf{y}) d\mathbf{y} = 0, \quad \mathbf{x} \in \partial B.$$

Using (3.11) we obtain

$$\int_B \Gamma_0(\mathbf{x}, \mathbf{y})(\nabla \cdot (\mathbf{J}_1 - \mathbf{J}_2))(\mathbf{y}) d\mathbf{y} = 0, \quad \mathbf{x} \in \partial B. \quad (3.23)$$

Note that $\Gamma_0(\mathbf{x}, \mathbf{y})$ is a harmonic function which decays at infinity (with order $\|\mathbf{x}\|^{-1}$) for $\mathbf{y} \in B$ and $\mathbf{x} \in \mathbb{R}^3 \setminus B$. We easily get

$$\int_B \Gamma_0(\mathbf{x}, \mathbf{y})(\nabla \cdot (\mathbf{J}_1 - \mathbf{J}_2))(\mathbf{y}) d\mathbf{y} = 0, \quad \mathbf{x} \in \mathbb{R}^3 \setminus B. \quad (3.24)$$

Recall the following addition formula for $\|\mathbf{x}\| > \|\mathbf{y}\|$ (see [8, 14])

$$\frac{1}{4\pi\|\mathbf{x} - \mathbf{y}\|} = \sum_{n=0}^{\infty} \sum_{m=-n}^n \frac{1}{2n+1} Y_n^m(\mathbf{x}/\|\mathbf{x}\|) \overline{Y_n^m(\mathbf{y}/\|\mathbf{y}\|)} \frac{\|\mathbf{y}\|^n}{\|\mathbf{x}\|^{n+1}}, \quad (3.25)$$

where Y_n^m denotes the spherical harmonic function of degree n and order m . By choosing $\mathbf{x} \in \partial\mathcal{B}_R$, where $\mathcal{B}_R$ is a sufficiently large ball such that $B \subseteq \mathcal{B}_R$, and inserting (3.25) into (3.24) and using the orthogonality of Y_n^m , we immediately conclude that

$$\int_B \|\mathbf{y}\|^n Y_n^m(\mathbf{y}/\|\mathbf{y}\|)(\nabla \cdot (\mathbf{J}_1 - \mathbf{J}_2))(\mathbf{y}) d\mathbf{y} = 0, \quad \mathbf{x} \in \partial\mathcal{B}_R. \quad (3.26)$$

Note that $\|\mathbf{y}\|^n Y_n^m(\mathbf{y}/\|\mathbf{y}\|)$, $m = -n, \dots, n$, $n = 0, 1, 2, \dots$, yield all the homogeneous harmonic polynomials. Hence (3.26) and the first case (i) in Definition 3.2 imply $\nabla \cdot (\mathbf{J}_1 - \mathbf{J}_2) = 0$; see also [13] for the relevant argument for a similar case in thermo and photoacoustic tomography. For the second case (ii) in Definition 3.2, since ϵ , μ and σ are constants in B , due to the rotational invariance of the Maxwell system (see [5]), without loss of generality, we can assume that $\mathbf{d} = (0, 0, 1)$ in the case (ii), which gives

$$\partial_{\mathbf{x}_3} \Phi(\mathbf{x}) = 0.$$

That is, Φ is independent of $\mathbf{x}_3$. Following a similar argument to the proof of Theorem 2.2 in [13] by using Fourier analysis techniques, we can show that (3.26) and the second case (ii) in Definition 3.2 also imply that $\nabla \cdot (\mathbf{J}_1 - \mathbf{J}_2) = 0$. By using (3.1) one can easily see that $\mathbf{E}_1 - \mathbf{E}_2 = \mathcal{O}(\omega)$ in B .

If $\mathbf{J}_j \in H(\text{div}; B)$, $j = 1, 2$, are curl-free functions, then by using the Helmholtz decomposition we have

$$\mathbf{J}_j = \nabla u_j, \quad j = 1, 2,$$

which together with $\nabla \cdot (\mathbf{J}_1 - \mathbf{J}_2) = 0$ and $\mathbf{J}_1 = \mathbf{J}_2 = 0$ on ∂B , readily implies that $\mathbf{J}_1 = \mathbf{J}_2$ in B . Next, by using integration by parts, we can obtain

$$\nabla \times \mathcal{V}_B^0[\mathbf{J}_j] = \mathcal{V}_B^0[\nabla \times \mathbf{J}_j] = 0, \quad j = 1, 2,$$

which shows that the second term in (2.50) vanishes. By (2.50) we have

$$\mathbf{H}_j = -i\omega\epsilon_0(I_3 - D^2\mathcal{V}_B^0\tilde{\mu}_j)^{-1}\nabla \times \mathcal{V}_B^0[\mathbf{E}_j] + \mathcal{O}(\omega^2), \quad j = 1, 2,$$

and hence

$$(I_3 - D^2\mathcal{V}_B^0\tilde{\mu}_j)[\mathbf{H}_j] = -i\omega\epsilon_0\nabla \times \mathcal{V}_B^0[\mathbf{E}_j] + \mathcal{O}(\omega^2), \quad j = 1, 2. \quad (3.27)$$

Noting that μ_j , $j = 1, 2$, are constants in B , and by taking divergence of both sides of (3.27), we can show that

$$\nabla \cdot \mathbf{H}_j = \mathcal{O}(\omega^2), \quad j = 1, 2.$$

Together with (3.20), or $\nu \cdot (\mu_1\mathbf{H}_1 - \mu_2\mathbf{H}_2) = 0$ on ∂B (see (3.14)), (3.27) and integration by parts we get

$$(\mathbf{H}_1 - \mathbf{H}_2)|_{\partial B}^- - \nabla \mathcal{S}_B^0[\nu \cdot (\mathbf{H}_1 - \mathbf{H}_2)|_{\partial B}^-] = \mathcal{O}(\omega^2). \quad (3.28)$$

By using the trace formula (2.12) we conclude that

$$(\mu_1^{-1} - \mu_2^{-1}) \left(\frac{3}{2}I - (\mathcal{K}_B^0)^* \right) [\nu \cdot \mathbf{H}_1|_{\partial B}^+] = \mathcal{O}(\omega^2).$$

Since (3.21) holds and $3/2I - (\mathcal{K}_B^0)^*$ is invertible on $L^2(\partial B)$ we finally obtain $\mu_1 = \mu_2$.

For the case (ii), if $\nabla \cdot \mathbf{J}_=0$ have from 2.49 that $\mathbf{E}_j = \mathcal{O}(\omega)$, $j = 1, 2$. By using (3.10) and noting that μ_j , $j = 1, 2$, are constants $\nabla \cdot \mathbf{H} = \mathcal{O}(\omega^2)$, and then by using (3.2) and integration by parts we further conclude that

$$\mathbf{H} = -\tilde{\mu} \nabla \mathcal{S}_B^0[(\nu \cdot \mathbf{H})|_{\partial B}^-] + \mathcal{V}_B^0[\nabla \times \mathbf{J}] + \mathcal{O}(\omega^2) \quad \text{in } B. \quad (3.29)$$

Hence by using (3.20) and (3.12) we get

$$-i(\tilde{\mu}_1 - \tilde{\mu}_2)\xi e^{i\mathbf{x} \cdot \xi} + \mathcal{V}_B^0[\nabla \times (\mathbf{J}_1 - \mathbf{J}_2)] = 0 \quad \text{on } \partial B.$$

Taking the inner product with ξ on both sides of the above equation (noting that $\xi \cdot \xi = 0$), we get

$$\mathcal{V}_B^0[\xi \cdot (\nabla \times (\mathbf{J}_1 - \mathbf{J}_2))] = 0 \quad \text{on } \partial B.$$

Thus by using the fact that $\xi \cdot (\nabla \times (\mathbf{J}_1 - \mathbf{J}_2))$ satisfies the admissibility condition in Definition 3.2 and similar analysis as that for (3.23), we can show that

$$\xi \cdot (\nabla \times (\mathbf{J}_1 - \mathbf{J}_2)) = 0 \quad \text{in } B.$$

Therefore $\nabla \times (\mathbf{J}_1 - \mathbf{J}_2)$ can be denoted by $\xi'g$, where $g \in L^2(B)^3$ and $\xi' \in \mathbb{C}^3$ satisfies

$$\begin{pmatrix} \Re \xi' \\ \Im \xi' \end{pmatrix} \in \mathbb{M}(\xi),$$

with $\mathbb{M}(\xi) \subset \mathbb{R}^6$ given by

$$\mathbb{M}(\xi) := \text{span} \left\{ \begin{pmatrix} \Re \xi \\ \Im \xi \end{pmatrix}, \begin{pmatrix} \Im \xi \\ -\Re \xi \end{pmatrix}, \begin{pmatrix} \Re \xi \times \Im \xi \\ 0 \end{pmatrix}, \begin{pmatrix} 0 \\ \Re \xi \times \Im \xi \end{pmatrix} \right\}.$$

Moreover, $\xi'g$ should satisfy that $\nabla g \cdot \xi' = 0$ and thus $g(\mathbf{x}) = \xi'' \cdot \mathbf{x}$, $\xi'' \in \mathbb{M}(\xi')$. To sum up, we have

$$\nabla \times (\mathbf{J}_1 - \mathbf{J}_2) = \xi'(\xi'' \cdot \mathbf{x}), \quad \xi' \in \mathbb{M}(\xi), \quad \xi'' \in \mathbb{M}(\xi').$$

Noting the fact that $\mathbf{J}_j = 0$ on ∂B , $j = 1, 2$, we immediately get that $\xi'(\xi'' \cdot \mathbf{x}) = 0$ and hence $\nabla \times (\mathbf{J}_1 - \mathbf{J}_2) = 0$. Together with the assumption that $\nabla \cdot \mathbf{J}_j = 0$, $j = 1, 2$, we conclude $\mathbf{J}_1 = \mathbf{J}_2$. By using (3.29) again, we can readily get that $\mu_1 = \mu_2$ and thus $\mathbf{H}_1 - \mathbf{H}_2 = \mathcal{O}(\omega^2)$ in B . Define $\mathbf{F}_j$ in B by

$$\mathbf{F}_j := \nabla \times \mathcal{V}_B^0[\tilde{\mu}_j \mathbf{H}_j] + (\mathcal{V}_B^0 + D^2 \mathcal{L}_B)[\mathbf{J}_j], \quad j = 1, 2, \quad (3.30)$$

then (2.51) can be reformulated as

$$(I_3 - D^2 \mathcal{V}_B^0 \tilde{\gamma}_j)[\mathbf{E}_j] = i\omega \mu_0 \mathbf{F}_j + \mathcal{O}(\omega^3), \quad j = 1, 2. \quad (3.31)$$

By integration by parts we then have that (noting that $\tilde{\gamma}_j$, $j = 1, 2$ are constants)

$$\mathbf{E}_j + \nabla \mathcal{S}_B^0[\nu \cdot \tilde{\gamma}_j \mathbf{E}_j|_{\partial B}^-] = i\omega\mu_0 \mathbf{F}_j + \mathcal{O}(\omega^3), \quad j = 1, 2$$

holds in B . Since we have already proved that $\mathbf{F}_1 - \mathbf{F}_2 = \mathcal{O}(\omega^2)$, by taking the trace of the above equation and using (3.20), or $\nu \cdot \epsilon_1 \mathbf{E}_1 = \nu \cdot \epsilon_2 \mathbf{E}_2$ on ∂B , we get

$$(\epsilon_1^{-1} - \epsilon_2^{-1}) \left(\frac{3}{2}I - (\mathcal{K}_B^0)^* \right) [\nu \cdot \mathbf{E}_1|_{\partial B}^+] = \mathcal{O}(\omega^3), \quad (3.32)$$

By using (3.32), the invertibility of $3/2I - (\mathcal{K}_B^0)^*$ on $L^2(\partial B)$, and the assumption (3.22), we have $\epsilon_1 = \epsilon_2$ and finally by the assumption that $\sigma_j = c\epsilon_j$, $j = 1, 2$, we have $\sigma_1 = \sigma_2$ and $\mathbf{E}_1 - \mathbf{E}_2 = \mathcal{O}(\omega^3)$.

The proof is complete. $\square$

Next, we present the second main theorem on the simultaneous recovery results when the medium parameters are piecewise constants (cf. Assumption 1).

Theorem 3.2. *Let $(\epsilon_1, \mu_1, \sigma_1, \mathbf{J}_1)$ and $(\epsilon_2, \mu_2, \sigma_2, \mathbf{J}_2)$ be two sets of permittivity, permeability, conductivity and source current. Suppose that $(\epsilon_j, \mu_j, \sigma_j)$ and $\mathbf{J}_j \in H_0(\text{div}; B)$ verify (2.5), $j = 1, 2$. Suppose further that $\mu_1 = \mu_2 = \mu'$ and $\nabla \cdot \mathbf{J}_1 = \nabla \cdot \mathbf{J}_2 = 0$ in B , where μ' is a positive constant, and ϵ_j and σ_j are piecewise constants in B which satisfy (2.28) in Assumption 1. Let $(\mathbf{E}_1, \mathbf{H}_1)$ and $(\mathbf{E}_2, \mathbf{H}_2)$ be the corresponding solutions to (2.3) and (2.4), associated with $(\epsilon_1, \mu_1, \sigma_1, \mathbf{J}_1)$ and $(\epsilon_2, \mu_2, \sigma_2, \mathbf{J}_2)$, respectively. Suppose that*

$$\Pi_{\epsilon_1, \mu_1, \sigma_1, \mathbf{J}_1}(\mathbf{x}, \omega) = \Pi_{\epsilon_2, \mu_2, \sigma_2, \mathbf{J}_2}(\mathbf{x}, \omega), \quad (\mathbf{x}, \omega) \in \partial B \times (0, \omega_0), \quad (3.33)$$

where ω_0 is any given positive constant. If there holds that

$$\nu \cdot \mathbf{E}_j|_{\partial B}^+ + \nu \cdot \mathbf{E}_j|_{\partial B}^+ \omega^{-1} + \nu \cdot \mathbf{E}_j|_{\partial B}^+ \omega^{-2} \neq 0 \quad \text{as } \omega \rightarrow +0, \quad (3.34)$$

$j = 1, 2$, then we have $\mathbf{J}_1 = \mathbf{J}_2$ and $\epsilon_1^{(1)} = \epsilon_2^{(1)}$ and $\sigma_1^{(1)} = \sigma_2^{(1)}$ provided there exists $\xi \in \mathbb{S}^2$ such that $\Phi := \xi \cdot (\nabla \times (\mathbf{J}_1 - \mathbf{J}_2))$ satisfies the admissibility condition in Definition 3.2. Furthermore, if there holds that

$$\nu \cdot \mathbf{E}_j|_{\partial \Sigma_l}^- \omega^{-1} \neq 0 \quad \text{as } \omega \rightarrow +0, \quad j = 1, 2 \quad (3.35)$$

then we have $\epsilon_1^{(l+1)} = \epsilon_2^{(l+1)}$ and $\sigma_1^{(l+1)} = \sigma_2^{(l+1)}$, $l = 1, 2, \dots, N$.

Proof. By following a similar proof as in the second case of Theorem 3.1, we can show $\mathbf{J}_1 = \mathbf{J}_2$ and $\mathbf{H}_1 - \mathbf{H}_2 = \mathcal{O}(\omega^2)$. We also have (3.31). By taking the divergence of both sides of (3.31), we conclude

$$\nabla \cdot ((1 + \tilde{\gamma}_j) \mathbf{E}_j) = \mathcal{O}(\omega^3), \quad j = 1, 2. \quad (3.36)$$

Together with the assumption that ϵ and μ are piecewise constants defined in (2.28) we can show that

$$\nabla \cdot \mathbf{E}_j = \mathcal{O}(\omega^3), \quad \text{in } \mathbb{R}^3 \setminus \left(\bigcup_{l=1}^{N+1} \partial \Sigma_{l-1} \right). \quad (3.37)$$

By using (3.13), (3.30) and (3.31) again, (3.37), the assumption (3.33), or

$$\nu \cdot ((\epsilon_1 + i\sigma_1/\omega)\mathbf{E}_1 - (\epsilon_2 + i\sigma_2/\omega)\mathbf{E}_2)|_{\partial B}^- = 0,$$

and integration by parts we can readily obtain

$$(\mathbf{E}_1 - \mathbf{E}_2)|_{\partial B}^- - \nabla \mathcal{S}_B^0[\nu \cdot (\mathbf{E}_1 - \mathbf{E}_2)|_{\partial B}^-] = \mathcal{O}(\omega^3). \quad (3.38)$$

Next, by taking the inner product of both sides of (3.38) with ν and using the trace formula, we have

$$((\epsilon_1^{(1)} + i\sigma_1^{(1)}\omega^{-1})^{-1} - (\epsilon_2^{(1)} + i\sigma_2^{(1)}\omega^{-1})^{-1}) \left(\frac{3}{2}I - (\mathcal{K}_B^0)^* \right) [\nu \cdot \mathbf{E}_1|_{\partial B}^+] = \mathcal{O}(\omega^3), \quad (3.39)$$

By the assumption (3.34), we have from (3.39) that

$$\epsilon_1^{(1)} + i\sigma_1^{(1)}\omega^{-1} = \epsilon_2^{(1)} + i\sigma_2^{(1)}\omega^{-1},$$

and thus

$$\epsilon_1^{(1)} = \epsilon_2^{(1)}, \quad \text{and} \quad \sigma_1^{(1)} = \sigma_2^{(1)}.$$

Hence by using (3.31) there holds $\mathbf{E}_1 - \mathbf{E}_2 = \mathcal{O}(\omega^3)$. Finally, using the transmission condition on $\partial \Sigma_l$ in Lemma 3.3 and (3.35), we can show that

$$(\epsilon_1^{(l+1)} - \epsilon_2^{(l+1)} + i(\sigma_1^{(l+1)} - \sigma_2^{(l+1)})\omega^{-1})\nu \cdot \mathbf{E}_1|_{\partial \Sigma_l}^- = \mathcal{O}(\omega^2),$$

and hence there hold $\epsilon_1^{(l+1)} = \epsilon_2^{(l+1)}$ and $\sigma_1^{(l+1)} = \sigma_2^{(l+1)}$, $l = 1, 2, \dots, N$.

The proof is complete. $\square$

ACKNOWLEDGMENT

The work of Y. Deng was supported by NSF grant of China, No. 11601528, Mathematics and Interdisciplinary Sciences Project, Central South University, and Innovation Program of Central South University, No. 10900-506010101. The work of H. Liu was supported by the FRG grants from Hong Kong Baptist University, Hong Kong RGC General Research Funds, 12302415, and the NSF grant of China, No. 11371. G. Uhlmann was partly supported by NSF.

REFERENCES

- [1] H. Ammari, G. Bao and J. Fleming, *An inverse source problem for Maxwell's equations in magnetoencephalography*, SIAM J. Appl. Math., **62** (2002), 1369–1382.
- [2] H. Ammari, Y. Deng, H. Kang and H. Lee, *Reconstruction of Inhomogeneous conductivities via the concept of generalized polarization tensors*, Ann. I. H. Poincaré-AN, **31** (2014), 877–897.

- [3] H. Ammari, H. Kang, *Polarization and Moment Tensors With Applications to Inverse Problems and Effective Medium Theory*, Applied Mathematical Sciences, Springer-Verlag, Berlin Heidelberg, 2007.
- [4] G. Bao, J. Lin and F. Triki, *A multi-frequency inverse source problem*, J. Differential Equations, **249** (2010), 3443–3465.
- [5] G. Bao, H. Liu and J. Zou, *Nearly cloaking the full Maxwell equations: cloaking active contents with general conducting layers*, J. Math. Pures Appl. (9), **101** (2014), no. 5, 716–733.
- [6] D. Cohen, *Magnetoencephalography: evidence of magnetic fields produced by alpha rhythm currents*, Science, **161** (1968), 784–786.
- [7] D. Cohen, *Magnetoencephalography: detection of the brain's electrical activity with a superconducting magnetometer*, Science, **175** (1972), 664–666.
- [8] D. Colton and R. Kress, *Inverse Acoustic and Electromagnetic Scattering Theory*, 2nd Edition, Springer-Verlag, Berlin, 1998.
- [9] A. S. Fokas, I. M. Gel'fand and Y. Kurylev, *Inversion method for magnetoencephalography*, Inverse Problems, **12** (1996), no. 3, L9–L11.
- [10] A. S. Fokas, Y. Kurylev and V. Marinakis, *The unique determination of neuronal currents in the brain via magnetoencephalography*, Inverse Problems, **20** (2004), 1067–1082.
- [11] V. Isakov, *Inverse Problems for Partial Differential Equations*, Springer, New York, 1998.
- [12] H. Liu, L. Rondi and J. Xiao, *Mosco convergence for $H(\text{curl})$ spaces, higher integrability for Maxwell's equations, and stability in direct and inverse EM scattering problems*, J. Eur. Math. Soc., to appear.
- [13] H. Liu and G. Uhlmann, *Determining both sound speed and internal source in thermo- and photo-acoustic tomography*, Inverse Problems, **31** 2015, 105005.
- [14] J. C. Nédélec, *Acoustic and Electromagnetic Equations: Integral Representations for Harmonic Problems*, Springer-Verlag, New York, 2001.
- [15] P. Ola, L. Päiväranta and E. Somersalo, *An inverse boundary value problem in electrodynamics*, Duke Math. J., **70** (1993), 617–653.
- [16] P. Ola and E. Somersalo, *Electromagnetic inverse problems and generalized Sommerfeld potentials*, SIAM J. Appl. Math., **56** (1996), 1129–1145.
- [17] P. Stefanov and G. Uhlmann, *Thermoacoustic tomography with variable sound speed*, Inverse Problems, **25** (2009), 075011.
- [18] P. Stefanov and G. Uhlmann, *Thermoacoustic tomography arising in brain imaging*, Inverse Problems, **27** (2011), 045004.
- [19] P. Stefanov and G. Uhlmann, *Instability of the linearized problem in multiwave tomography of recovery both the source and the speed*, Inverse Problems and Imaging, **7** (2013), 1367–1377.
- [20] J. Sylvester and G. Uhlmann, *A global uniqueness theorem for an inverse boundary value problem*, Ann. of Math. (2), **125** (1987), 153–169.
- [21] G. Uhlmann, *Developments in inverse problems since Calderón's foundational paper*, Ch. 19 in *Harmonic Analysis and Partial Differential Equations*, M. Christ, C. Kenig and C. Sadosky, eds., University of Chicago Press (1999), 295–345.
- [22] G. Uhlmann, ed., *Inside Out: Inverse Problems and Applications*, MSRI Publications, Vol. 47, Cambridge University Press, 2003.

SCHOOL OF MATHEMATICS AND STATISTICS, CENTRAL SOUTH UNIVERSITY,
CHANGSHA, HUNAN, P. R. CHINA.

E-mail address: youjundeng@csu.edu.cn, dengyijun_001@163.com

DEPARTMENT OF MATHEMATICS, HONG KONG BAPTIST UNIVERSITY, KOWLOON,
HONG KONG SAR

E-mail address: hongyu.liuip@gmail.com

DEPARTMENT OF MATHEMATICS, UNIVERSITY OF WASHINGTON, SEATTLE,
WA 98195, USA/ JOCKEY CLUB INSTITUTE FOR ADVANCED STUDY, HKUST,
HONG KONG SAR / DEPARTMENT OF MATHEMATICS AND STATISTICS, UNIVER-
SITY OF HELSINKI, FINLAND

E-mail address: gunther@math.washington.edu